



**Schaltsteckdose**

Diese Steckdoseneinheit ist zum Anschluss an einen Relaisausgang des ELM Systems geeignet. Sie dient zum Schalten von Netzstromgeräten.

3000-U41-00 Kabelende mit offenen Kontakten

3000-U41-01 mit Stecker für ELM 19"-Einschübe oder ELM Box-Module

Technische Änderungen vorbehalten.



**Switch Power Socket**

This power socket can be connected to a relay output of the ELM system. It is used to switch mains power of plugged-in devices.


3000-U41-00 cable ends with open contacts

3000-U41-01 with connector plug for ELM 19"-racks or ELM box modules

Subject to technical changes.



Fig. 1: 3000-U41-01

Plug front side view	Pin number of plug	Signal	Wire color
	1	Contact	white
	2	Contact	brown
	3	(not used)	-
	4	(not used)	-

**Lamp:**

The lamp is connected in parallel connection to the power output. It is on when plugged device is switched on.

**Characteristics**

- Outlet system: ..... Type F, CEE 7/4 Schuko (German 2-pin, side clip earth)
- Power input: ..... 200 ... 250 V AC, 47...63 Hz
- Power output switching: ..... max. 10 A
- Control input: ..... switched off → approx. 12 V DC, switched on → max. 50 mA
- Dimensions: ..... 120 x 65 x 55 mm<sup>3</sup>
- Cable length: ..... 3 m